



OPERATING MANUAL
FOR
HDMI SPLITTER (4K)

Milestone Electronics Pvt. Ltd.

HDMI SPLITTER (4K)

HDMI SPLITTER (4K) by Milestone is a device that helps person to display any HDMI Source i.e. computers, laptops, DVD player, DVR, camera with multiple projectors or monitor or LCD or Plazma having HDMI Port providing simultaneous display.

Models available

ML 102 HDMI-4K	1 input with 2 HDMI outputs
ML 104 HD-4K	1 input with 4 HDMI outputs
ML 108 HD-4K	1 input with 8 HDMI outputs

Features

INSTALLATION	Easy to install - plug and play kind. <ul style="list-style-type: none">● HDTV Compatible● Can work with DVI inputs & outputs● Uses Equalization & re-clocking technology.
SHARING	1 Input with multiple projectors or monitor or LCD or Plazma
COMPATIBILITY	Fully compatible to 4K HDMI Ports, 4Kx2K@60Hz. 4:2:0 & supports 3 D format
INDICATION	LED indication for working set &
COMPLIANCE	HDCP 1.4

SPECIFICATIONS

MODEL	ML 102 HDMI-4K	ML 104 HD-4K	ML 108 HD-4K
INPUT CONNECTORS	HDMI × 1	HDMI × 1	HDMI × 1
OUTPUT CONNECTOR	HDMI × 2	HDMI × 4	HDMI × 8
LED INDICATION	1, 2 and PWR	1 to 4 and PWR	1 to 8 and PWR
MAINS INPUT (DC) ADAPTOR	5V/1A	5V/1A	5V/2A
DIMENSION TABLE TOP (mm)	59 x 63 x 20	182 x 101x 51	310 x 115 x 51
WEIGHT	400 g	800 g	1000 g

OPERATION: -

- 1) Connect HDMI source & displays into the splitter.
- 2) Connect DC adaptor power supply to the splitter.
- 3) Turn ON the Power.
- 4) When all “input & outputs” are connected and turned on, the corresponding LEDS will light.

Note: - For ML 108HD-4K, connect lowest resolution TV at Output Port No. 1. At anytime the Input will detect the resolution from Port No.1 & set the resolution.

PRECAUTIONS: -

- 1) Please insert HDMI Cable gently.
- 2) Do not turn on the power. Switch of the splitter before input source and output displays are attached.

---X---X---X---X---