



*OPERATING MANUAL*  
*FOR*  
*HDMI SPLITTER &*  
*AUDIO DEEMBEDDER*  
**(4K@60Hz/ARC/AUDIO EDID)**

Milestone Electronics Pvt. Ltd.

## **HDMI SPLITTER & AUDIO DEEMBEDDER (4K)**

HDMI SPLITTER & AUDIO DEEMBEDDER (4K) by Milestone is a device that helps person to display any HDMI Source i.e. computers, laptops, DVD player, DVR, camera with two projector or monitor or LCD or Plazma having HDMI Port providing simultaneous display with deembedded audio for connection to Audio Amplifier. One HDMI O/P is ARC Supported.

### **Models available**

ML 102 HDA-ARC-4K	1HDMI Input with 2 HDMI OUTPUTS & 1 Analog & 1 Toslink Audio O/P
-------------------	---

### **Features**

<b>INSTALLATION</b>	Easy to install - plug and play kind. <ul style="list-style-type: none"> <li>● HDTV Compatible</li> <li>● Can work with DVI inputs &amp; outputs</li> <li>● Uses Equalization &amp; re-clocking technology.</li> </ul>
<b>SHARING</b>	1 Input with 2 projector or monitor or LCD or Plazma with Deembedded Audio (Analog & TOS Link)
<b>COMPATIBILITY</b>	Fully compatible to 4K HDMI Ports, 4Kx2K@60Hz. 4:4:4 & supports 3D, Dolby format. Can be scaled down to 1080P.
<b>INDICATION</b>	LED indication for working set
<b>COMPLIANCE</b>	HDCP 1.4
<b>HDMI ARC SUPPORT</b>	Output1 supports ARC

## SPECIFICATIONS

<b>MODEL</b>	<b>102 HDA-ARC-4K</b>
<b>INPUT CONNECTORS</b>	HDMI × 1
<b>OUTPUT CONNECTOR</b>	HDMI × 1 HDMI ARC X 1 Analog Stereo Audio RCA x1 TOS Link Audio x1
<b>LED INDICATION</b>	PWR-1 Audio 2 CH-1 Audio 5.1CH-1 Audio Pass-1 ARC-1 HDMI IN-1 HDMI OUT 1-1 HDMI OUT 2-1 Audio ON/OFF-1
<b>SWITCHES</b>	Audio ON/OFF-1 ARC ON/OFF-1 AUDIO EDID-1
<b>MAINS INPUT (dc) ADAPTOR</b>	5V/1A
<b>DIMENSION TABLE TOP (mm)</b>	(140 x 70 x 25)
<b>WEIGHT</b>	300 gms

### 1) AUDIO EDID SETTING

With Audio EDID Switch 2.1, 5.1 & pass through Audio format can be selected which is indicated by LED's.

### 2) ARC ON/OFF SWITCH

With ARC/ON/OFF Switch, ARC mode is switched On or OFF indicated by ARC LED.

### 3) AUDIO ON/OFF

With Audio ON/OFF Switch Audio Out (i.e TOSLINK &RCA) are disabled indicated by LED.

## **OPERATION: -**

- 1) **ARC OFF Mode: -**
- 2) Connect HDMI source, displays & Audio Amplifier to the splitter.
- 3) Connect DC adaptor power supply to the splitter.
- 4) Turn ON the Power.
- 5) When all “input & outputs” are connected and turned on, the corresponding LEDS will light.
- 6) Set EDID of Audio as required.
- 7) In ARC off mode, TOSLINK & Stereo Audio O/P Port works as de-embedder Audio out.

## **II) ARC ON Mode: -**

- 1) Connect HDMI Source at input of unit. Connect HDMI Out 1 (ARC Port) to ARC Port of display. Connect HDMI OUT2 to HDMI port of second TV.
- 2) In ARC Model whatever is played ON TV, you will get audio out from TOSLINK & Stereo Audio.

## **PRECAUTIONS: -**

- 1) Please insert HDMI Cable gently.
- 2) Please use Proper Adaptor-5V/1Amp.

