



*OPERATING MANUAL*  
*FOR*  
***HDMI SPLITTER (4K)***

Milestone Electronics Pvt. Ltd.

## HDMI SPLITTER (4K)

HDMI SPLITTER (4K) by Milestone is a device that helps person to display any HDMI Source i.e. computers, laptops, DVD player, DVR, camera with multiple projector or monitor or LCD or Plasma having HDMI Port providing simultaneous display.

### Models available

ML 102 HDMI-4K	1 input with 2 HDMI outputs
ML 104 HDMI-4K	1 input with 4 HDMI outputs
ML 108 HDMI-4K	1 input with 8 HDMI outputs

### Features

<b>INSTALLATION</b>	Easy to install - plug and play kind. <ul style="list-style-type: none"><li>● HDTV Compatible</li><li>● Can work with DVI inputs &amp; outputs</li><li>● Uses Equalization &amp; re-clocking technology.</li></ul>
<b>SHARING</b>	1 Input with multiple projector or monitor or LCD or Plasma
<b>COMPATIBILITY</b>	Fully compatible to 4K HDMI Ports, 4Kx2K@60Hz. 4:2:0 & supports 3 D format
<b>INDICATION</b>	LED indication for working set &
<b>COMPLIANCE</b>	HDCP 1.4

## SPECIFICATIONS

<b>MODEL</b>	<b>102 HDMI-4K</b>	<b>104 HDMI-4K</b>	<b>108 HDMI-4K</b>
<b>INPUT CONNECTORS</b>	HDMI × 1	HDMI × 1	HDMI × 1
<b>OUTPUT CONNECTOR</b>	HDMI × 2	HDMI × 4	HDMI × 8
<b>LED INDICATION</b>	1, 2 and PWR	1 to 4 and PWR	1 to 8 and PWR
<b>MAINS INPUT (DC) ADAPTOR</b>	5V/1A	5V/1A	5V/2A
<b>DIMENSION TABLE TOP (mm)</b>	59 x 63 x 20	182 x 101x 51	310 x 115 x 51
<b>WEIGHT</b>	400 g	800 g	1000 g

## **OPERATION: -**

- 1) Connect HDMI source & displays into the splitter.
- 2) Connect DC adaptor power supply to the splitter.
- 3) Turn ON the Power.
- 4) When all “input & outputs” are connected and turned on, the corresponding LEDS will light.

**Note:** - For ML 108HDMI-4K, connect lowest resolution TV at Output Port No. 1. At anytime the Input will detect the resolution from Port No.1 & set the resolution.

## **PRECAUTIONS: -**

- 1) Please insert HDMI Cable gently.
- 2) Do not turn on the power. Switch of the splitter before input source and output displays are attached.

