



***OPERATING MANUAL
FOR
VIDEO SPLITTER***

Milestone Electronics Pvt. Ltd.

VIDEO SPLITTER

The Video Multiplier/Splitter by Milestone is a device that helps users to send Video output to as many LCD/TFT with ability for many display output.

Models available

ML 102 V	1 Composite Video input 2 Composite Video outputs
ML 104 V	1 Composite Video input 4 Composite Video outputs
ML 108 V	1 Composite Video input 8 Composite Video outputs
ML 112 V	1 Composite Video input 12 Composite Video outputs
ML 116 V	1 Composite Video input 16 Composite Video outputs

Features

- 1) 1 Input to many outputs, each individually amplified.
- 2) Rugged metal enclosure.
- 3) Adjustable gain.
- 4) 230V AC Power (500mA for 102V, 104V)
(1Amp for 108V, 112V, 116V)

SPECIFICATIONS

Bandwidth	250MHZ(-3db)
Gain	adjustable

Video input :

Number /Signaltype	1 Composite Video
Connectors	1RCA female (Optional BNC)
Nominal level	1V P-P for composite video
Minimum /Maximum Level	Analog: 0.4V to 1.4V P-P with no offset at unity gain.
Impedance	75ohms

Video Output:

Number /Signal type	Composite Video
Connectors	RCA female (Optional BNC)
Nominal level	1 V P-P for composite video
Minimum /Maximum Level	0.4V to 1.4V P-P for composite video
Impedance	75ohms

